



Installation & Maintenance Manual  
Fieldbus system - Digital unit  
Type 56-EX600-DX□□-X10  
56-EX600-DY□□-X10

56-EX600-DX□B-X10  
56-EX600-DX□C□-X10  
II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C  
II 3D Ex tc IIIC T82 °C Dc X IP67

56-EX600-DX□D-X10  
II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C  
II 3D Ex tc IIIC T86 °C Dc X IP67

56-EX600-DY□B-X10  
II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C  
II 3D Ex tc IIIC T68 °C Dc X IP67

Safety Instructions (Continued)

Warning

- Do not disassemble, modify (including changing the printed circuit board) or repair.  
An injury or failure can result.
- Do not operate or set with wet hands.  
This may lead to an electric shock.
- Do not operate the product outside of the specifications.  
Do not use for flammable or harmful fluids.  
Fire, malfunction, or damage to the product can result.  
Verify the specifications before use.
- Do not operate in an atmosphere containing flammable or explosive gases for long periods.  
Fire or an explosion can result.  
This product is suitable for ATEX category 3 only.
- If using the product in an interlocking circuit:
  - Provide a double interlocking system, for example a mechanical system.
  - Check the product regularly for proper operation.  
Otherwise malfunction can result, causing an accident.
- The following instructions must be followed during maintenance:
  - Turn off the power supply.
  - Stop the air supply, exhaust the residual pressure and verify that the air is released before performing maintenance.  
Otherwise an injury can result.

Caution

- When handling, assembling or replacing the unit:
  - Avoid touching any sharp metal parts of the connectors for connecting units.
  - When assembling units, take care not to get any fingers caught between units. Injury can result.
  - When disassembling units, take care to avoid excessive force.  
The connection parts of the unit are firmly joined with seals and injury can result.

- After maintenance is complete, perform appropriate functional inspections.  
Stop operation if the equipment does not function properly.  
Safety cannot be assured in the case of unexpected malfunction.
- Provide grounding to assure the noise resistance of the Fieldbus system.  
Individual grounding should be provided close to the product with a short cable.

ATEX Marking Description

II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C  
II 3D Ex tc IIIC T?? °C Dc X IP67

Equipment Group II	tc - protected by enclosure
Category 3	IIIC - for all types of dust
Gas (G) and Dust (D) environment	T?? °C - max. surface temperature
Ex - European standards apply	Gc/Dc - Equipment Protection Level
nA - Non-sparking apparatus	X - special conditions apply, see instructions
IIC - for all types of gas	Ta - ambient temperature
T4 - Temperature classification	IP67 - protection structure


Special Conditions Notes

- The product should be used within the range of specifications given below and in the product catalogue.  
If labelled with X special conditions apply:
1. Protect the product from sources of heat which can generate surface temperatures higher than the temperature classification.
  2. Protect the product and cables against all impact or mechanical damage using a suitable ATEX compliant enclosure.
  3. Protect the product from direct sunlight or UV light using a suitable protective cover.
  4. Do not disconnect the connectors before first switching off the power supply.
  5. Use only ATEX approved connectors and use only shielded cable to provide grounding.
  6. Use only a damp cloth to clean the product body, to avoid an electrostatic charge.


Summary of Product parts

Digital input unit


•56-EX600-DX□B-X10



•56-EX600-DX□C□-X10




•56-EX600-DX□D-X10



Digital output unit

•56-EX600-DY□B-X10






No.	Description	Function
1	Status display LED	Displays the status of the unit.
2	Connector	Connector for inputs or outputs, using M12 or M8 connector.
3	Marker groove	Groove to mount a marker.
4	Joint bracket	Bracket for joining to adjacent units.
5	Unit connector (Plug)	Transmits signals and power supplies to adjacent units.

Assembly

Assembling the unit as a manifold

- (1) Connect a unit to the end plate.  
Digital and Analogue I/O units can be connected in any order.  
Tighten the joint brackets to a torque of 1.5 to 1.6 Nm.
- (2) Add more I/O units.  
Up to 10 units (including the SI unit) can be connected to one manifold.
- (3) Connecting the SI unit.  
After connecting the required I/O units, connect the SI unit.  
The method is as above in (1), (2).
- (4) Mounting the valve plate.  
Mount the valve plate (EX600-ZMV□) to the valve manifold using the valve set screws. (M3x8)  
Apply 0.6 to 0.7 Nm tightening torque to the screws.
- (5) Connect the SI unit to the valve manifold.  
Insert the valve plate into the valve plate mounting groove on the side of the SI unit.  
Fix using the valve plate screws (M4x6) supplied, to a torque of 0.7 to 0.8 Nm.




Mounting and Installation

Installation

Direct mounting

- (1) When joining six or more units, fix the middle part of the complete EX600 unit with an intermediate reinforcing brace (EX600-ZMB1) before mounting, using 2-M4x5 screws.  
Tightening torque: 0.7 to 0.8 Nm.




- (2) Mount and tighten the end plate at one end of the unit. (M4)  
Tightening torque: 0.7 to 0.8 Nm.  
Fix the end plate at the valve side while referring to the operation manual of the corresponding valve manifold.


DIN rail mounting

(Not available for SY series valves. Refer to the SY catalogue.)

- (1) When joining six or more units, fix the middle part of the complete EX600 unit with an intermediate reinforcing brace (EX600-ZMB2) before mounting, using 2-M4x6 screws.  
Tightening torque: 0.7 to 0.8 Nm.




- (2) Mount the end plate bracket (EX600-ZMA2) to the end plate at the opposite end to the valves, using 2-M4x14 screws.  
Tightening torque: 0.7 to 0.8 Nm.



Mounting and Installation (Continued)


(3) Hook the DIN rail mounting groove on to the DIN rail.



(4) Press the manifold using its side hooked to the DIN rail as a fulcrum until the manifold is locked.

(5) Fix the manifold by tightening the DIN rail fixing screws of the EX600-ZMA2. (M4x20)  
Tightening torque:  
0.7 to 0.8 Nm.

The tightening torque at the valve side depends on the valve type.  
Refer to the operation manual of the corresponding valve manifold.



Mounting and Installation (Continued)

•Connector pin assignment

•Digital input unit

Configuration		Pin number	Signal name
56-EX600-DX□B-X10	56-EX600-DX□C□-X10		
		1	24 V (Control and input)
		2	Input 2
		3	0 V (Control and input)
		4	Input 1
		5	FE

•Digital output unit

Configuration	Pin number	Signal name	
56-EX600-DY□B-X10		56-EX600-DYPB-X10	56-EX600-DYNB-X10
	1	NC	24 V (Output)
	2	Output 2	Output 2
	3	0 V (Output)	NC
	4	Output 1	Output 1
	5	FE	FE

Maintenance

- Maintenance should be performed according to the Safety Instructions.
- Perform regular maintenance and inspections.  
There is a risk of unexpected malfunction.
- Do not use solvents such as benzene, thinner etc. to clean each unit.  
They could damage the surface of the body and erase the markings on the body.
- Use a soft cloth to remove stains.  
For heavy stains, use a cloth soaked with diluted neutral detergent and fully squeezed, then wipe up the stains again with a dry cloth.

Refer to the SMC website (URL <http://www.smcworld.com>) to obtain more detailed information about maintenance.


Troubleshooting

Refer to the LED Display. Refer to the SMC website (URL <http://www.smcworld.com>) to obtain more detailed information about troubleshooting.

■Wiring


•Connect the M12 connector cable.  
The M12 SPEEDCON connector connection method is explained below.

- (1) Align mark B on the metal bracket of the cable connector (plug/socket) with mark A.
- (2) Align with mark C on the unit and insert the connector vertically.  
If they are not aligned, the connector cannot be connected correctly.
- (3) When mark B has been turned 180 degrees (1/2 turn), wiring is complete. Confirm that the connection is not loose. If turned too far, it will become difficult to remove the connector.



•Identification marker

The signal name of the input or output devices and unit address can be written on the marker, and can be installed on each unit.  
Mount the marker (EX600-ZT1) into the marker groove as required.



LED Display

•Digital input unit

ST: SStatus display LED

Model	Display	Content
56-EX600-DX□B-X10 56-EX600-DX□C□-X10 56-EX600-DX□D-X10	OFF.	The power supply for control and input, or the input device, is OFF.
	Green LED is ON.	The input device is ON.
	Red LED is ON.	The input device has a short circuit.
	Red LED is flashing.	Either of the following conditions: •The input device ON/OFF count has exceeded the set value. •The input device is open circuit. (Only for EX600-DX□C1)

•Digital output unit

ST: SStatus display LED

Model	Display	Content
56-EX600-DY□B-X10	OFF.	The power supply for control and input, or the output device, is OFF.
	Green LED is ON.	The output device is ON.
	Red LED is ON.	The output device has a short circuit.
	Red LED is flashing.	Either of the following conditions: •The output device ON/OFF count has exceeded the set value. •The output device is open circuit.

Specification

Model		56-EX600-DX□B-X10 56-EX600-DX□C-X10 56-EX600-DX□D-X10	56-EX600-DY□B-X10
Power supply	Control and input	24 VDC, 2 A	
	Output	-	24 VDC, 2 A
Rated input current		9 mA or less	-
Max. load current		-	500 mA or less/output
Operating temperature range		-10 to 50 °C (Max. surrounding air temperature rating: 50 °C)	
Storage temperature range		-20 to 60 °C	
ATEX Classification		56-EX600-DX□B-X10 56-EX600-DX□C□-X10 II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C II 3D Ex tc IIIC T82 °C Dc X IP67 56-EX600-DX□D-X10 II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C II 3D Ex tc IIIC T86 °C Dc X IP67 56-EX600-DY□B-X10 II 3G Ex nA IIC T4 Gc X -10 °C≤Ta≤50 °C II 3D Ex tc IIIC T68 °C Dc X IP67	
Vibration resistance		10 to 57 Hz: constant amplitude 0.75 mm p-p 57 to 150 Hz: constant acceleration 49 m/s² for 2 hours each in direction X, Y and Z respectively (De-energized)	
Impact resistance		147 m/s² 3 times each in directions of X, Y and Z respectively (De-energized)	

\*1: Input terminals are not isolated from Power source.

\*2: Do not connect outside Power source to Input and Output terminals.

Specification (Continued)

Refer to the product catalogue or SMC website (URL <http://www.smcworld.com>) to obtain more detailed information about product specifications.

Outline with Dimensions

Refer to the product catalogue or SMC website (URL <http://www.smcworld.com>) to obtain more detailed information about outline dimensions.

Contacts

AUSTRIA	(43) 2262 62280-0	LATVIA	(371) 781 77 00
BELGIUM	(32) 3 355 1464	LITHUANIA	(370) 5 264 8126
BULGARIA	(359) 2 974 4492	NETHERLANDS	(31) 20 531 8888
CZECH REP.	(420) 541 424 611	NORWAY	(47) 67 12 90 20
DENMARK	(45) 7025 2900	POLAND	(48) 22 211 9600
ESTONIA	(372) 651 0370	PORTUGAL	(351) 21 471 1880
FINLAND	(358) 207 513513	ROMANIA	(40) 21 320 5111
FRANCE	(33) 1 6476 1000	SLOVAKIA	(421) 2 444 56725
GERMANY	(49) 6103 4020	SLOVENIA	(386) 73 885 412
GREECE	(30) 210 271 7265	SPAIN	(34) 945 184 100
HUNGARY	(36) 23 511 390	SWEDEN	(46) 8 603 1200
IRELAND	(353) 1 403 9000	SWITZERLAND	(41) 52 396 3131
ITALY	(39) 02 92711	UNITED KINGDOM	(44) 1908 563888

SMC Corporation

URL <http://www.smcworld.com> (Global) <http://www.smceu.com> (Europe)

Specifications are subject to change without prior notice from the manufacturer.  
© 2010-2016 SMC Corporation All Rights Reserved.